

APP PC5933T

n. 1

| | |
|----------------|--|
| Factory Name | APP PC5933T |
| Description | Vertical contact MINI P/ CLAW APP PC5933T type |
| Other features | - |



APP30 1317G4

n. 2


| | |
|----------------|---|
| Factory Name | APP30 1317G4 / PP30 1327BK / PP30 1327G6BK |
| Description | APP30 1317G4 type |
| Other features | APP30 MOUNTING WINGS 1399G8BK type – Black: PP30 1327G6BK APP – Red: PP30 1327BK APP – Vert. contact PP30 1317G4 APP – Mounting: PP30 MOUNTING WINGS 1399G8BK APP |



AMP 75

n. 3

| | |
|----------------|--|
| Factory Name | AMP 201311-3 |
| Description | HV multipin connector |
| Other features | Mates with AMP 201310 cable connector; suitable for operation in the -55 ÷ +150 °C range |



Radiall 52

n. 4

| | |
|----------------|--|
| Factory Name | Radiall 691 803 004 |
| Description | HV multipin connector |
| Other features | Mates with Radiall 691 802 002 and CAEN Mod. A996 cable connectors; up to 9 kV supported |



SHV

n. 5

| | |
|----------------|----------------------|
| Factory Name | Radiall R317580 |
| Description | HV coaxial connector |
| Other features | Supports up to 10 kV |



CPE 3 Pole

n. 6

| | |
|----------------|-------------------------------|
| Factory Name | CPE 28-019 |
| Description | HV 3 Pin Panel Male Connector |
| Other features | supports up to 18 kV |



CPE HV

n. 7

| | |
|----------------|--|
| Factory Name | CPE 23.100.151.046 |
| Description | HV Coaxial Connector |
| Other features | supports up to 18 kV; mates with HV Cable Connector CPE 23.100.052.045 |



DB37

n. 8


| | |
|----------------|-----------------------|
| Factory Name | FCI DCPV37S300GT |
| Description | DB37 Female connector |
| Other features | - |



Brass hexagon head bolt

n. 9


| | |
|----------------|---------------------------------------|
| Factory Name | RS Stock no. 483-2390 |
| Description | Brass hexagon head set screw, M6x30mm |
| Other features | - |



Robinson Nugent 68 pin boardmount connector

n. 10


| | |
|----------------|--|
| Factory Name | 3M P50E-068P1-SR1-TG |
| Description | Robinson Nugent 68 pin straight angle thru-hole boardmount connector |
| Other features | Mates with Robinson Nugent P50E-068S-TG wiremount connector |



Header-type connectors

n. 11

| | |
|----------------|--|
| Factory Name | 3M 3431-6202 (17+17 pin); 3M 3408-5202 (8+8 16 pin) |
| Description | Header-type connector |
| Other features | Available with different pin sets; the 17+17 connector mates with 3M 3414-6600 wiremount connector |



LEMO

n. 12

| | |
|----------------|-----------------------------|
| Factory Name | Fischer DP101A004-51 |
| Description | LEMO type coaxial connector |
| Other features | - |



BNC

n. 13


| | |
|----------------|----------------------------|
| Factory Name | Radiall R141603 |
| Description | BNC type coaxial connector |
| Other features | - |



Strip Header

n. 14

| | |
|----------------|---|
| Factory Name | AMP 5/826634/0 (17+17 pin) |
| Description | Male strip header (17+17 pin) |
| Other features | the 17+17 connector mates with 3M 3414-6600 wiremount connector |



USB

n. 15

| | |
|----------------|--------------|
| Factory Name | AMP 787780-2 |
| Description | USB Type B |
| Other features | - |



LC

n. 16

| | |
|----------------|--------------------------|
| Factory Name | Agilent HFBR-5911L/AL |
| Description | LC type duplex connector |
| Other features | - |



LEMO EPG0B

n. 17

| | |
|----------------|-----------------|
| Factory Name | EPG.0B.302.HLN |
| Description | LEMO 2 pin type |
| Other features | - |



MCX connector

n. 18

| | |
|----------------|-------------------------|
| Factory Name | SUHNER CS 85MCX-50-0-16 |
| Description | 50 Ohm MCX connector |
| Other features | - |

